

The Imaging Source Helpdesk

Knowledgebase > Software > Software for Windows > Very simple open device and show live video in C++

Very simple open device and show live video in C++

S.Geißler - 2019-05-27 - Software for Windows

In case you use Microsoft Visual Studio C++ and IC Imaging Control 3.4, then you start at <https://theimagingsource.deskpro.com/en/kb/articles/creating-a-visual-studio-c-project-with-ic-imaging-control>

IC Imaging Control 3.4 can be downloaded from <https://www.theimagingsource.com/support/downloads-for-windows/software-development-kits-sdks/icimagingcontrol/>

The main() is simple:

```
int main(int argc, char* argv[])
{
    DShowLib::InitLibrary();

    atexit( ExitLibrary );

    Grabber grabber;

    grabber.openDev("DFK 33UX183");

    if( !grabber.isDevValid() )
    {
        return -1;
    }

    grabber.setVideoFormat("RGB24 (640x480)");

    grabber.startLive();

    std::cout << "Press any key to continue!" << std::endl;

    std::cin.get();

    grabber.stopLive();

    return 0;
}
```

In case you use another C++ environment and the C Wrapper DLL from <https://www.theimagingsource.com/support/downloads-for-windows/software-development-kits-sdks/icimagingcontrol/>

[kits-sdks/tisgrabberdll/](#):

```
#include <stdio.h>

#include <conio.h>

#include <tisgrabber.h>

int main()

{

    HGRABBER hGrabber; // The handle of the grabber object.

    IC_InitLibrary(NULL);

    hGrabber = IC_CreateGrabber();

    if( hGrabber )

    {

        IC_OpenVideoCaptureDevice(hGrabber,"DMK 23UV024");

        if( IC_IsDevValid(hGrabber))

        {

            IC_SetVideoFormat(hGrabber,"RGB24 (640x480)");

            IC_StartLive(hGrabber,1);

            printf("Press any key to stop the live video\n" );

            _getch();

            IC_StopLive(hGrabber);

        }

        IC_ReleaseGrabber(&hGrabber);

    }

    return 0;

}
```

If you use Microsoft Visual Studio C++, then IC Imaging Control is recommended, because it is more sophisticated.